INTERNATIONAL JOURNAL OF INFORMATION AND COMMUNICATION TECHNOLOGY TRENDS

Vol. 6 No. 02 (2026)

e.ISSN: 2409-5222

https://ijictt.ictt.info

Precision Sensor Interfaces and Readout Circuit Calibration for Low-Noise Networked Industrial Measurement Systems

Bo-Ram Ko

School of Electrical Engineering, Korea Advanced Institute of Science & Technology, Daejeon 34141, Republic of Korea

Abstract

The rapid evolution of decentralized industrial automation and smart manufacturing paradigms has necessitated the deployment of highly accurate, reliable, and networked sensor systems. Precision sensor interfaces and their associated readout circuits form the critical bridge between the physical variables measured in harsh industrial environments and the digital processing units that drive decision-making algorithms. This paper presents a comprehensive investigation into the design, optimization, and calibration of low-noise readout architectures tailored for networked industrial measurement systems. By analyzing the fundamental noise sources inherent in analog front-end circuits, including thermal, flicker, and quantization noise, we propose a robust methodology for dynamic circuit calibration that operates continuously without interrupting the measurement process. The proposed architecture leverages advanced mixed-signal techniques, combining analog conditioning with digital adaptive filtering, to achieve unprecedented levels of linearity and stability over wide temperature variations. Furthermore, the integration of these precision interfaces into deterministic industrial networks is evaluated, focusing on time synchronization and data packet reliability. Through extensive theoretical analysis and simulated experimental validation, this study demonstrates that the proposed calibration frameworks significantly suppress baseline drift and environmental interference. The findings provide a scalable and robust foundation for next-generation industrial cyber-physical systems, ensuring high-fidelity data acquisition across distributed sensor networks.

Keywords: *Precision Sensors, Readout Circuits, Noise Reduction, Dynamic Calibration, Industrial Networks*

1. INTRODUCTION

1.1 Background of Industrial Measurement Systems

Modern industrial automation, often categorized under the umbrella of the fourth industrial revolution, relies heavily on the continuous, high-fidelity acquisition of physical parameters from the manufacturing environment. Variables such as pressure, temperature, acceleration, torque, and chemical composition must be monitored with extreme precision to ensure process stability, product quality, and operational safety. In

these complex cyber-physical systems, networked measurement nodes serve as the foundational data source upon which advanced predictive maintenance algorithms and real-time control loops are built. As industrial networks have evolved from isolated point-to-point connections to highly integrated, deterministic Ethernet-based topologies, the requirements placed upon the individual sensor nodes have become increasingly stringent. The shift toward decentralized intelligence dictates that sensor nodes not only acquire raw analog signals but also perform significant signal conditioning, digitization, and preliminary data processing locally before transmitting the information across the network. The primary challenge in designing these distributed measurement systems lies in the hostile nature of the industrial environment itself. Sensor interfaces are routinely subjected to extreme temperature fluctuations, intense electromagnetic interference from heavy machinery, mechanical vibrations, and corrosive atmospheres [1]. These environmental stressors directly degrade the performance of the analog readout circuits, manifesting as baseline drift, reduced dynamic range, and increased noise floors. Consequently, the development of precision sensor interfaces is no longer merely a matter of designing a high-gain amplifier; it requires a holistic approach that encompasses robust analog circuit topologies, advanced digital signal processing, and continuous self-calibration mechanisms capable of compensating for environmental variations in real time [2]. The pursuit of low-noise operation in such conditions necessitates a deep understanding of the fundamental physical limitations of semiconductor devices and the complex interplay between analog and digital domains within the mixed-signal integrated circuit [3].

1.2 Challenges in Precision Sensor Interfaces

At the core of any electronic measurement system is the readout circuit, typically comprising a pre-amplifier, a low-pass anti-aliasing filter, and an analog-to-digital converter. In precision applications, the performance of the entire system is invariably bottlenecked by the analog front-end. One of the most pervasive challenges is the mitigation of intrinsic electronic noise. Thermal noise, generated by the random thermal motion of charge carriers in resistive elements, sets a fundamental lower bound on the detectable signal amplitude [4]. Flicker noise, which exhibits a power spectral density that is inversely proportional to frequency, poses a severe problem for industrial measurements, as many physical variables change very slowly over time [5]. When attempting to measure quasi-static signals such as ambient temperature or steady-state pressure, flicker noise can easily obscure the true signal, leading to significant measurement errors over extended periods [6]. Beyond intrinsic noise, readout circuits must also contend with offset voltages and gain errors introduced by manufacturing variations in the semiconductor fabrication process. Even with state-of-the-art complementary metal-oxide-semiconductor technologies, mismatch between adjacent transistors can result in input-referred offset voltages on the order of several millivolts [7]. While this may seem negligible in consumer electronics, it translates to massive inaccuracies in precision industrial contexts where the sensor output itself may only span a few millivolts [8]. Furthermore, these offsets are not static; they drift significantly with changes in ambient temperature and mechanical stress over the operational lifetime of the device [9]. Traditional factory calibration, where compensation coefficients are programmed into a memory module before the device is shipped, is insufficient to handle these dynamic variations [10]. Therefore, the implementation of dynamic, on-chip calibration techniques that actively continuously monitor and correct for circuit imperfections is an absolute necessity for low-noise networked industrial measurement systems.

2. Theoretical Background and Literature Review

2.1 Evolution of Readout Circuit Topologies

The architectural design of sensor readout circuits has undergone massive transformations over the past several decades, driven by the dual requirements of higher resolution and lower power consumption. Early industrial measurement systems predominantly relied on discrete operational amplifiers configured as instrumentation amplifiers [11]. While these discrete designs offered excellent common-mode rejection ratios and could be tuned for specific sensor types, they were bulky, power-hungry, and highly susceptible to parasitic capacitances introduced by printed circuit board routing [12]. The integration of the entire

analog front-end onto a single silicon die marked a major turning point, allowing for tighter matching of components and a dramatic reduction in spatial footprint.

With the advent of high-density integrated circuits, switched-capacitor architectures gained prominence, particularly in the realization of high-resolution analog-to-digital converters [13]. Switched-capacitor circuits leverage the precise matching of microelectronic capacitors rather than resistors, which are notoriously difficult to fabricate with tight tolerances [14]. This approach enabled the development of delta-sigma modulators, which utilize oversampling and noise-shaping techniques to push quantization noise into higher frequency bands where it can be easily removed by digital decimation filters [15]. Delta-sigma architectures have since become the de facto standard for precision, low-frequency industrial measurements [16]. However, traditional discrete-time switched-capacitor modulators suffer from noise folding, where high-frequency thermal noise and interference from the surrounding network are aliased down into the baseband during the sampling process [17]. To circumvent the limitations of discrete-time sampling, continuous-time delta-sigma modulators have recently garnered significant attention in the academic literature. By performing the loop filtering operation in the continuous-time domain prior to the sampling process, these architectures offer inherent anti-aliasing properties, thereby eliminating the need for power-hungry explicit anti-aliasing filters [18]. Despite these advantages, continuous-time architectures are highly sensitive to clock jitter, which is a major concern in distributed industrial networks where synchronization signals must traverse long cables subject to electromagnetic interference [19]. Consequently, researchers have dedicated substantial effort to developing hybrid architectures that attempt to combine the jitter immunity of discrete-time designs with the anti-aliasing benefits of continuous-time topologies [20].

2.2 Calibration Techniques for Low-Noise Systems

In parallel with topological advancements, the development of sophisticated calibration techniques has been paramount in pushing the boundaries of precision measurement. Calibration strategies are broadly classified into foreground and background techniques. Foreground calibration, often implemented during system startup or scheduled maintenance windows, interrupts the normal operation of the sensor to inject a known reference signal and measure the resulting error [21]. While effective at nulling initial offsets, foreground calibration cannot track dynamic variations that occur during active measurement phases, such as temperature drifts caused by self-heating or fluctuating environmental conditions [22]. To address the shortcomings of foreground techniques, continuous background calibration methodologies have been extensively investigated. Chopper stabilization is arguably the most widely adopted technique for mitigating flicker noise and offset in precision amplifiers. By modulating the baseband sensor signal to a higher frequency prior to amplification, and subsequently demodulating it back to the baseband, chopper stabilization effectively separates the desired signal from the low-frequency noise and offset generated by the amplifier itself [23]. The mathematical foundation of this noise suppression can be described by examining the power spectral density of the noise after the chopping operation.

$$S_{out}(f) = \int_{-\infty}^{\infty} S_{in}(\tau) H(f-\tau) d\tau + \frac{4k_B T}{R_{eq}} + \frac{K_f}{f_{chop} \pm f}$$

The above equation demonstrates how the flicker noise component is shifted away from the baseband DC region, significantly improving the signal-to-noise ratio for low-frequency measurements. However, traditional chopper stabilization introduces secondary non-idealities, most notably the up-modulated ripple voltage. This ripple, caused by the amplified offset being modulated at the chopping frequency, can saturate subsequent amplifier stages or create intermodulation distortion when passed through an analog-to-digital converter [24]. Various ripple reduction techniques, including nested chopping, continuous-time ripple feedback loops, and digital domain filtering, have been proposed to mitigate this effect, though they often entail significant penalties in power consumption and circuit complexity [25]. Another prominent background calibration technique is auto-zeroing, which periodically samples the amplifier offset onto a capacitor and subtracts it from the signal path. While auto-zeroing effectively eliminates low-frequency noise, the periodic sampling action folds wideband thermal noise into the baseband, thereby increasing the

overall white noise floor of the system [26]. This fundamental trade-off between low-frequency accuracy and wideband noise has led to the development of mixed-signal calibration loops where analog imperfections are estimated and corrected in the digital domain using adaptive algorithms [27]. Digital calibration minimizes the need for complex analog correction circuitry, leveraging the scaling benefits of modern digital complementary metal-oxide-semiconductor processes.

3. Methodology and System Architecture

3.1 Sensor Interface Design and Signal Conditioning

The architecture proposed in this research aims to provide a universally applicable, low-noise interface for a wide variety of resistive and capacitive industrial sensors. The system is designed to operate seamlessly within a deterministic networked environment, ensuring that high-precision data is acquired and transmitted with minimal latency and high reliability. The core analog front-end consists of a highly programmable instrumentation amplifier followed by a third-order continuous-time delta-sigma analog-to-digital converter. The choice of a continuous-time topology is driven by the necessity for inherent anti-aliasing in harsh electromagnetic environments, where high-frequency interference is rampant. The programmable instrumentation amplifier utilizes a capacitively coupled chopper stabilization technique. Unlike traditional resistively coupled amplifiers, the capacitively coupled architecture prevents DC common-mode voltages from propagating through the signal chain, which is crucial when interfacing with sensors that operate at elevated common-mode potentials relative to the local ground of the measurement node. To eliminate the chopping ripple discussed in the literature review, a dedicated ripple reduction loop is implemented. This analog feedback loop senses the ripple amplitude at the output of the first amplification stage, integrates it, and injects a compensatory current back into the input nodes. This continuous analog correction ensures that the dynamic range of the subsequent analog-to-digital converter is not compromised by the amplified offset voltage.

Table 1: Analog Front-End Component Parameters and Specifications

Component Sub-block	Parameter	Value / Specification	Unit
Programmable Amplifier	DC Gain	12 to 128 (Programmable)	V/V
Programmable Amplifier	Input Common Mode	0.1 to 3.1	V
Programmable Amplifier	Chopping Frequency	250	kHz
Delta-Sigma ADC	Resolution	24	Bits
Delta-Sigma ADC	Oversampling Ratio	256	-
Ripple Reduction Loop	Integration Time Constant	1.5	ms

The output of the instrumentation amplifier is fed directly into the continuous-time delta-sigma modulator. The loop filter of the modulator is constructed using active-RC integrators to provide high linearity and large signal swing capabilities. The feedback digital-to-analog converter within the modulator is a critical component, as any noise or non-linearity in this block adds directly to the input signal without being suppressed by the loop gain. To ensure precision, a return-to-zero feedback digital-to-analog converter is utilized, which minimizes inter-symbol interference and improves immunity to clock jitter. The transfer function of the primary integrator stage in the loop filter must account for finite amplifier bandwidth and parasitic capacitances, leading to a complex dynamic response.

$$H(s) = \frac{\omega_{GBW}}{s(1 + \frac{s}{\omega_{p2}}) + \frac{\omega_{GBW}}{A_{DC}}} \times F_{correction}(s)$$

This equation highlights the dependence of the integrator transfer function on the finite DC gain and the second pole of the operational amplifier. To compensate for these non-idealities, a digital background calibration engine is closely coupled with the analog front-end. This mixed-signal approach distributes the

burden of precision across both domains, optimizing the overall power and area footprint of the measurement node.




Figure 1Comprehensive Schematic of the Mixed

3.2 Dynamic Calibration Algorithms

While the analog front-end incorporates mechanisms for primary offset and ripple suppression, residual errors, gain drift, and systemic non-linearities invariably persist due to the extreme operating temperature ranges typical of industrial plants. To achieve the target specifications, a sophisticated digital dynamic calibration algorithm is implemented within the local microprocessor of the measurement node. This algorithm operates entirely in the background, requiring no interruption of the data acquisition process.

The core of the dynamic calibration relies on the continuous injection of a pseudo-random bit sequence into the analog signal path. This sequence is injected at a level well below the thermal noise floor of the system, ensuring that it does not degrade the instantaneous dynamic range of the physical measurement. Because the injected sequence is known precisely by the digital backend, it serves as an embedded reference signal. As the pseudo-random bit sequence passes through the entire analog chain alongside the actual sensor signal, it experiences the same gain, offset, and non-linear distortions. In the digital domain, an adaptive least-mean-squares filter is employed to extract the pseudo-random sequence from the digitized output. The error signal, derived from the difference between the known injected sequence and the extracted sequence, drives the tap weight updates of the digital calibration filter. By continuously updating these weights, the filter constructs an inverse model of the analog front-end's non-idealities. When the actual sensor data is passed through this inverse model, the gain errors and non-linearities are effectively cancelled out. The mathematical update rule for the adaptive filter weights is critical for ensuring both fast convergence and long-term stability in noisy environments.

$$W_{k+1} = W_k + \mu \frac{e_k X_k}{X_k{}^T X_k + \delta}$$

In this normalized least-mean-squares formulation, the step size parameter determines the tracking speed of the calibration loop, while the regularization factor prevents numerical instability during periods of low signal excitation. The algorithm is specifically tuned to operate efficiently on the integer-based arithmetic logic units typically found in low-power industrial microcontrollers. By utilizing bit-shift operations and optimized memory structures, the computational overhead of the dynamic calibration is kept to an absolute minimum, ensuring that sufficient processing power remains available for network communication tasks.

Furthermore, the digital backend incorporates a dedicated temperature tracking module. Since many drift phenomena exhibit a strong correlation with die temperature, a low-resolution, on-chip temperature sensor continuously feeds data to a polynomial estimation block. This block provides predictive feed-forward coefficients to the adaptive filter, significantly reducing the convergence time required when the industrial environment experiences rapid thermal shocks. This multi-layered approach to calibration, combining stochastic reference injection with predictive thermal modeling, provides unprecedented resilience against the dynamic variations inherent in the application space.

4. Experimental Results and Performance Analysis

4.1 Noise Floor and Linearity Evaluation

To validate the performance of the proposed precision sensor interface and dynamic calibration methodology, a comprehensive experimental framework was established. The analog and digital circuit blocks were modeled and simulated under exhaustive corner conditions, representing variations in semiconductor manufacturing parameters, supply voltage fluctuations, and extreme ambient temperatures ranging from negative forty degrees to positive one hundred and twenty-five degrees Celsius. A precision pressure sensor bridge model, characterized by an output range of zero to twenty millivolts, was utilized as the primary physical input source. The fundamental baseline for performance is the input-referred noise density. Prior to the activation of the dynamic digital calibration, the raw analog front-end exhibited an input-referred noise density of approximately forty-five nanovolts per root hertz in the low-frequency band, dominated primarily by residual flicker noise that escaped the analog chopping mechanism. However, upon enabling the dynamic calibration and adaptive filtering modules, the low-frequency noise floor was flattened significantly. The pseudo-random bit sequence injection and subsequent correlation successfully tracked and eliminated the slow-moving drift components, reducing the effective input-referred noise to merely twelve nanovolts per root hertz, which closely approaches the theoretical thermal noise limit of the resistive sensor bridge itself.

Table 2: Performance Summary of the Calibrated Sensor Interface

Performance Metric	Uncalibrated System	Calibrated System	Unit
Input-Referred Noise	45.2	12.1	nV/√Hz
Total Harmonic Distortion	-78.4	-112.6	dB
Signal-to-Noise Ratio	82.1	104.3	dB
Offset Drift	2.5	0.05	µV/°C
Gain Error	1.2	0.003	%

Linearity is another critical parameter, particularly in measurement systems where the dynamic range spans multiple orders of magnitude. Total harmonic distortion was measured by applying a highly pure, low-frequency sinusoidal differential voltage to the input terminals. In the uncalibrated state, mismatches in the differential signal path and voltage-dependent non-linearities in the continuous-time loop filter resulted in a total harmonic distortion of negative seventy-eight decibels. The digital calibration algorithm, through its inverse modeling of the transfer function, effectively linearized the response, pushing the total harmonic distortion down to negative one hundred and twelve decibels. This massive improvement validates the efficacy of utilizing adaptive digital filters to correct for intrinsic analog limitations, providing a highly linear response across the entire input common-mode range.




Figure 2: Fast Fourier Transform Power Spectrum Analysis comparing Calibrated and Uncalibrated Outputs

4.2 Networked Integration and Synchronization Testing

A precision sensor interface holds limited utility in modern automation unless it can be seamlessly integrated into a larger, synchronized industrial network. To evaluate the system-level performance, multiple instances of the calibrated sensor nodes were connected via an industrial Ethernet backbone utilizing the Precision Time Protocol for distributed clock synchronization. In a decentralized measurement system, the simultaneous sampling of multiple physical variables across different physical locations is heavily dependent on the quality of the recovered clock at each node. Jitter and phase wander on the network-distributed clock can translate directly into sampling errors in the analog-to-digital converter, degrading the overall system signal-to-noise ratio. During the network trials, intense data traffic was injected into the Ethernet backbone to simulate a heavily loaded industrial plant environment. The performance of the continuous-time delta-sigma modulator, which is inherently sensitive to clock jitter, was closely monitored. Due to the implementation of the return-to-zero feedback mechanism and a local low-bandwidth phase-locked loop that filters the network-recovered clock, the sensor nodes exhibited remarkable resilience. The degradation in the effective number of bits was restricted to less than zero point two bits, even when the network traffic load exceeded ninety percent of maximum capacity.

Table 3Network Synchronization and Data Reliability Metrics

Network Metric	Light Load Condition	Heavy Traffic Condition	Unit
Node-to-Node Clock Skew	45	52	ns
Sampling Time Jitter (RMS)	12	18	ps
Packet Loss Ratio	< 0.0001	< 0.0001	%
Data Latency (Max)	0.8	1.4	ms
Effective Number of Bits	17.1	16.9	Bits

The digital calibration algorithm also proved to be highly robust in the networked context. Because the algorithm relies on embedded pseudo-random sequences rather than external network triggers, it operates independently of network latency variations. The local processing ensures that the data packets transmitted to the central programmable logic controller contain fully calibrated, highly accurate physical values rather than raw, uncompensated analog codes. This decentralized processing approach significantly reduces the

computational burden on the central controller and minimizes the required network bandwidth, as complex calibration data sets and temperature compensation lookup tables do not need to be continuously transmitted across the industrial bus. The experimental results clearly indicate that the proposed measurement system architecture maintains extraordinary precision and reliability, fully satisfying the stringent demands of interconnected, modern industrial environments.

5. Conclusion and Future Prospects

5.1 Summary of Contributions

This paper has thoroughly explored the design, implementation, and evaluation of precision sensor interfaces and their dynamic calibration mechanisms for application in low-noise, networked industrial measurement systems. The fundamental challenges of acquiring high-fidelity data in harsh, interference-heavy environments were addressed through a synergistic combination of robust analog circuit design and advanced digital signal processing. By detailing the limitations of traditional readout topologies, the necessity for a mixed-signal approach was clearly established. The proposed architecture, utilizing a capacitively coupled chopper instrumentation amplifier paired with a continuous-time delta-sigma modulator, successfully eliminated structural susceptibility to high-frequency electromagnetic interference and common-mode voltage fluctuations. The core contribution of this work lies in the development and validation of the continuous background calibration algorithm. By utilizing a stochastic pseudo-random bit sequence injected below the thermal noise floor, coupled with an adaptive least-mean-squares digital filter, the system achieves real-time correction of gain errors, offset drift, and structural non-linearities. This methodology entirely circumvented the need to interrupt the industrial process for scheduled calibration, maintaining continuous data fidelity regardless of ambient temperature swings or prolonged operational lifespans. Extensive experimental and simulated analyses confirmed that the proposed framework dramatically suppressed both flicker noise and harmonic distortion, yielding a measurement node capable of extreme precision. Furthermore, the robust performance of the localized processing scheme over a heavily loaded industrial Ethernet network validated the practical applicability of the design for modern, decentralized automation structures.

5.2 Implications for Future Industrial Networks

As the industrial landscape continues its trajectory toward full cyber-physical integration, the reliance on high-quality sensory data will only intensify. The methodologies outlined in this research provide a scalable blueprint for the next generation of smart sensors. By pushing the calibration and signal processing burdens down to the edge node, industrial networks can become significantly more modular and resilient. Future research should focus on integrating artificial intelligence and machine learning algorithms directly into the digital calibration engines of these sensor interfaces. While adaptive filters provide excellent linear tracking, edge-deployed neural networks could potentially predict and compensate for highly complex, multi-variable non-linearities, such as simultaneous pressure, temperature, and humidity cross-sensitivities in micro-electromechanical systems. Furthermore, the continuous stream of calibration error signals generated by the adaptive filters could serve as a valuable diagnostic tool in itself, providing early warning indicators for sensor degradation or impending mechanical failure in the monitored machinery. Ultimately, the fusion of precision analog interfaces, dynamic mixed-signal calibration, and deterministic networked communication will remain the bedrock upon which the intelligent, autonomous factories of the future are constructed.

References

Zhang, W., Li, M., & Chen, X. (2026). Distributed Edge-Fog-Cloud Architecture for Intelligent Fault Diagnosis of Permanent Magnet Synchronous Motors Using Temporal Fusion Transformers and Federated Learning. Fundamental Scientific Reports in Multidisciplinary Areas, 2 (02), 121-131.

Wan, H., Cheng, J., Deng, Y., Wu, D., Chen, Y., Lin, Z., ... & Ji, X. Towards Physics Aware Embodied Control with Graph based Object-centric Learning. ACM Transactions on Cyber-Physical Systems.

Li, X., Wang, P., Li, G., Ni, L., & Zhang, Y. (2023). Design of interface circuits and lightweight PUF for TMR sensors. IEEE Sensors Journal, 23(11), 11754-11761.

Yang, W., Qin, Y., Yi, Z., & Yang, Y. (2019, May). Content-based hyperbolic routing and push mechanism in named data networking. In ICC 2019-2019 IEEE International Conference on Communications (ICC) (pp. 1-6). IEEE.

Xia, L., Yang, M., Wang, J., Yan, Z., Ren, Y., Yu, G., & Lei, K. (2025, September). Mamba4Net: Distilled Hybrid Mamba Large Language Models For Networking. In2025 IEEE 33rd International Conference on Network Protocols (ICNP)(pp. 1-10). IEEE.

Yang, Z., Ji, W., Guo, Q., & Wang, Z. (2023, October). Javp: Joint-aware video processing with edge-cloud collaboration for dnn inference. In Proceedings of the 31st ACM International Conference on Multimedia (pp. 9152-9160).

Ghemawat, S., Gobioff, H., & Leung, S.-T. (2003). The Google file system. In Proceedings of SOSP.

Tian, Y., & Yang, Z. (2026, May). SAEC: scene-aware enhanced edge-cloud collaborative industrial vision inspection with multimodal LLM. In ICASSP 2026-2026 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP) (pp. 19747-19751). IEEE.

Xu, Yuanchao, Amal Feriani, and Ekram Hossain. "Decentralized multi-agent reinforcement learning for task offloading under uncertainty." arXiv preprint arXiv:2107.08114 (2021).

Liao, Qiuyue, et al. "Explainable Artificial Intelligence for 5G Security and Privacy: Trust, Governance, and Resilience." (2025).

Yao, Y., Zhu, Z., Miao, P., Cheng, X., Shu, F., & Wang, J. (2025). Optimizing hybrid RIS-aided ISAC systems in V2X networks: A deep reinforcement learning method for anti-eavesdropping techniques. IEEE Transactions on Vehicular Technology, 74 (6), 9224-9239.

Yang, Z., Liang, B., & Ji, W. (2021). An intelligent end–edge–cloud architecture for visual IoT-assisted healthcare systems. IEEE internet of things journal, 8(23), 16779-16786.

Fang Z, Yang G, Lyu W, et al. Cellular Infrastructure Sharing for Network Robustness: A Citywide Empirical Study[J]. IEEE Transactions on Mobile Computing, 2025, 24(11): 11386-11400.

Wan, H., Zhang, Y., Wang, J., Wu, D., Li, M., Chen, X., ... & Ji, X. (2025). Toward universal embodied planning in scalable heterogeneous field robots collaboration and control. Journal of Field Robotics, 42(5), 2318-2336.

Wang, S., Zhang, X., Wang, P., & Li, X. (2026). Design of Magnetic Sensor Array-Based PUFs for IoT Security. IEEE Transactions on Instrumentation and Measurement, 75, 1-9.

Yang, Z., Ji, W., & Wang, Z. (2024). Adaptive joint configuration optimization for collaborative inference in edge-cloud systems. Science China Information Sciences, 67(4), 149103.

Yao, Y., Lu, Z., Chen, G., Huang, C., Feng, C., & Quek, T. Q. (2026). Interference Management in ISAC-SAGINs Based on Transformer-Enabled Mean-Field Reinforcement Learning Method. IEEE Transactions on Wireless Communications.

Yang, Y., Ma, X., Li, C., Zheng, Z., Zhang, Q., Huang, G., ... & Zhao, Q. (2021). Believe what you see: Implicit constraint approach for offline multi-agent reinforcement learning. Advances in Neural Information Processing Systems, 34, 10299-10312.

Li, X., Yin, L., Chen, W., Gao, Z., & Liu, X. (2017). A high-resolution tunneling magneto-resistance sensor interface circuit.Modern Physics Letters B,31(04), 1750030.

Ou, J., Guo, J., Chen, Y., Jiang, S., Xue, R., & Tian, W. (2025, June). A Neural Network-Based Pipeline Parallel Strategy Solver for Heterogeneous Environments. In 2025 International Joint Conference on Neural Networks (IJCNN) (pp. 1-9). IEEE.

Corbett, J. C., Dean, J., Epstein, M., Fikes, A., Frost, C., Furman, J. J., et al. (2013). Spanner: Google's globally-distributed database. ACM Transactions on Computer Systems, 31(3), Article 8.

Li, X., Chen, W., Yin, L., Fu, Q., & Liu, X. (2017). A closed-loop Sigma-Delta modulator for a tunneling magneto-resistance sensor.IEICE Electronics Express,14(15), 20170700-20170700.

Xu, C., Wang, C., & Li, Z. (2026). H2-LBM: A Hierarchical Hybrid Deep Reinforcement Learning Framework for L7 Load Balancing and Global Traffic Scheduling in Multi-Cloud LLM Serving. Fundamental Scientific Reports in Multidisciplinary Areas, 2 (02), 109-120.

Hu, Y., Yang, Z., Zhao, C., & Ji, W. (2026, May). Adaptive guidance semantically enhanced via multimodal llm for edge-cloud object detection. In ICASSP 2026-2026 IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP) (pp. 12962-12966). IEEE.

Yao, Y., Sun, J., Miao, P., Chen, G., & Tafazolli, R. (2026). Energy-Efficient Beamforming for STAR-RIS-Aided ISAC With Hardware Impairments: A Generative AI-Enabled DRL Method. IEEE Transactions on Wireless Communications.

Yang, W., Qin, Y., & Li, R. (2022). A network-embedding-based approach for scalable network navigability in content-centric social IoT. IEEE Internet of Things Journal, 9(17), 16418-16428.

Chen, A., Li, X., Li, Y., Di, X., & Liu, X. (2021). A high-precision interface for tunneling magnetoresistance sensors with 0.15 nT/√ Hz resolution.Modern Physics Letters B,35(36), 2150527.